

Bon Jour Unplugged NEW

Designed by Philippe Starck, 2015



3W - 150lm - 2200-2700-3000K - CRI> 90


Cordless table lamp providing direct light. Injection moulded body and PMMA clear transparent diffuser. Edge Lighting technology light source. 6/24 hours battery life, rechargeable with USB C and Qi. Optical switch sensor on the base that provide 4-step dimming function and Color temperature control on 3-steps (2200K, 2700K and 3000K). USB-C charger cable included in the package useful length 120 cm



Mounting	Portable
Light source type	LED
Light sources included	Yes
LED type	LED Module
Power (W)	3
Lumen Output (lm)	150

Physical

Colour	Almost White
Length (mm)	110
Net weight (kg)	0.45
Package height (mm)	200
Package width (mm)	160
Package length (mm)	365
Package volume (m3)	0.01
IP internal	20



ø131 mm

ø103 mm

Download

Mounting instructions



Ecodesign and Energy Labelling

This product contains a light source of energy efficiency class **G**





Replaceable (LED only) light source by a professional



















https://professional.flos.com/en/global/product/bon-jour-unplugged-f1040009/

F1040009

Photometric

Lighting type	Direct
Light distribution	Roto symmetric
CCT (K)	2200-2700-3000
CRI>	90
Extreme cut off	No

Electrical

Insulation class	III
Main voltage (Vac)	5
Power supply	Remote excluded
Dimmable	Yes
Dimming interface	Dimmer Integrated
Induction recharge QI	Yes
Batteries inside	Yes
Battery type	LI-IO
Charging cycles guaranteed	500
Charging min time	3
Charging socket/connector	USB-C

Accessories & Power Supply









OPTIONAL

F1036007

Bon Jour Unplugged Crown

OPTIONAL

F1036030

Bon Jour Unplugged Crown

OPTIONAL

F1036070

Bon Jour Unplugged Crown

OPTIONAL

F1036088

Bon Jour Unplugged Crown

Spare Parts



O1. Bon Jour Unplugged Ivory Top
 Cover
O2. Bon Jour Unplugged Crown
 F1036000
 Bon Jour Unplugged Base
 assembly with battery kit







RF37016

Bon Jour Unplugged Ivory Top Cover =1036000

Bon Jour Unplugged Crown

RF1040100

Bon Jour Unplugged Base assembly with battery kit